

6.6 A Current Controlled Halogen - Pk30d Base Lamps for Series Operation


Области применения


- Airfield Lighting



CBP_09.00 Product features and benefits, all [calc.]

- Low maintenance costs due to long lamp life
- Reliable and consistent light output enhances visibility over the life of the lamp
- FAA approved in conjunction with many OEM fixtures
- Durable construction provides resistance to the effects of vibration
- Broad product portfolio for runway, taxiway, and approach lighting
- IR radiation provides guidance in low visibility conditions
- Flicker-free operation
- Ability to reduce light output when needed
- Mercury-free





Connector A, female

PK30d Connector A female

Product family datasheet

Technical data

Product description	LIF	Electrical Data		Lifetime Data [GMS]
		Nominal wattage	Nominal voltage	
64319 Z/C 45-15	-	45 W	6.8 V	1500 hr
64317 C 45-15	J1/76	45 W	6.8 V	1500 hr
64317 IRC-C 45-30	J1/76	45 W	120 V	3000 hr
64318 A 45-15	J1/77	45 W	6.8 V	1500 hr
64328 HLX-A 65-15	-	65 W	9.8 V	1500 hr
64328 HLX-Z/C 65-15	-	65 W	9.8 V	1500 hr
64341 HLX-A 100-15	J1/79	100 W	15.2 V	1500 hr
64341 HLX-Z/C 100-15	J1/79	100 W	15.2 V	1500 hr
64342 HLX-C 100-15	J1/80	100 W	15.2 V	1500 hr
64361 HLX-A150-15	J1/83	150 W	22.7 V	1500 hr
64361 HLX-Z/C150-15	J1/83	150 W	22.7 V	1500 hr
64382 HLX-A 200-15	J1/84	200 W	30.3 V	1500 hr
64318 Z/C 45-15	J1/77	45 W	6.8 V	1500 hr
64319 A 45-15	-	45 W	6.8 V	1500 hr
64382 HLX-C 200-15	J1/84	200 W	30.3 V	1500 hr

Product family datasheet

Советы по безопасности

To prevent personal injury or damage to property, halogen lamps may only be operated in suitable luminaires designed with suitable mechanisms (protective shields, grids, etc.) to ensure that in the event of a lamp bursting no parts/shards can escape and that during operation no ultraviolet radiation can escape. There must also be a warning sign to indicate that the lamps give off high levels of heat. Detailed information is available on request.

Application advice

For more detailed application information and graphics please see product datasheet.

Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.