

## Lok-it! Power Series (PS)



### Области применения

- Concert Lighting
- Club & Disco
- Stage & Theatre
- Studio, TV, & Film
- Architecture & Architainment

### CBP\_09.00 Product features and benefits, all [calc.]

- Compact design and short arc gap allows for smaller and brighter fixtures
- Fast lamp replacement with one-touch rotate and lock base and socket design
- Robust design with eXtreme Seal (XS) technology, allowing up to 450°C at the pinch seal
- Consistent lumen output over the life of the lamp
- Improved ceramic base allows high voltage up to 35kV
- Higher luminous efficacy than conventional HID lamps provides higher fixture efficiency
- Power series offers enhanced performance features and versatility, including BRILLIANT lamps with high CRI and BLUE lamps that offer 7500K for bright white light



Product family datasheet

Technical data

Product description	Electrical Data		Photometric Data	
	Nominal wattage [calc.]	Nominal voltage [calc.]	Nominal luminous flux [calc.]	Color temperature [calc.]
Lok-it! 1000/PS	1000 W	85 V	85000 lm	6000 K
Lok-it! 1000/PS Brilliant	1000 W	85 V	82000 lm	6000 K
Lok-it! 1400/PS Brilliant	1400 W	95.5 V	118000 lm	6000 K
Lok-it! 1700/PS	1700 W	84.5 V	135000 lm	6000 K
Lok-it! 1800/PS Brilliant	1800 W	88 V	148000 lm	6000 K
Lok-it! 2000/PS Brilliant	2000 W	108 V	165000 lm	6000 K

Product description	Lifetime Data
	Average Rated Life [GMS]
Lok-it! 1000/PS	950 hr
Lok-it! 1000/PS Brilliant	750 hr
Lok-it! 1400/PS Brilliant	750 hr
Lok-it! 1700/PS	750 hr
Lok-it! 1800/PS Brilliant	750 hr
Lok-it! 2000/PS Brilliant	750 hr

## Product family datasheet

---

### Советы по безопасности

Because of their high luminance, UV radiation and high internal pressure during operation, Lok-it! lamps may only be operated in enclosed lamp casings specially constructed for the purpose. Appropriate filters must ensure that UV radiation is reduced to an acceptable level. Mercury is released if the lamp breaks. Special safety precautions must be taken. Information on safety and handling is available on request or can be found in the leaflet included with the lamp or in the operating instructions.

---

### Application advice

For more detailed application information and graphics please see product datasheet.

---

### Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.